



www.alfatronelectronics.com

ALFATRON ELECTRONICS GmbH GERMANY

YouTube and Facebook Live Streaming Guide


Streaming to YouTube

Please read the following steps to stream to YouTube.

Step 1:


Connect the camera to your network and make sure the network settings are correct according to your network. Choose DHCP, or set your own IP address and DNS

Camera default IP is 192.168.5.163 and the Subnet of 255.255.255.0.



Step 2:

Create your event on YouTube and get the following information.



YouTube will give you two parameters, "stream key" and "stream URL"


Step 3:

Fill these two parameters into the "Host Address" and "Stream Name" of the camera. Then click enable and save.

1. Please update the camera with the latest firmware (www.alfatronelectronics.com)
2. Copy the Stream url into the Host Address Field
3. Change the port number to 1935
4. Insert the Stream Key into the Stream Name Field
5. Click Enable and Save


NOTE: Please use the following format when inserting the Stream url into the HOST Address on the camera. Please Remove rtmp:// and /live2. As per below Image

NOTE: Please use the following format when inserting the Stream key into the Stream Name on the camera. live2/"Stream Key". As per Below image



Step 4:


If the camera has an audio input, please enable on the settings on the camera.



Follow the camera prompts to reboot the camera for the settings to take effect.

Step 5:

Once it has been set up as per above, the stream will be live on YouTube.




Streaming to Facebook

Please read the following steps to stream to Facebook.

Step 1:


Connect the camera to your network and make sure the network settings are correct according to your network. Choose DHCP, or set your own IP address and DNS.

Camera default IP is 192.168.5.163 and the Subnet of 255.255.255.0.



Step 2:

Start a live video stream on Facebook and get the following information from Facebook.



The screenshot shows the 'Live Stream Setup' interface. It includes a title 'Live Stream Setup', a subtitle 'Copy and paste these settings into your streaming software.', and two main sections: 'Server URL' and 'Stream Key'. Each section has a text input field with a 'Copy' button to its right. Below the 'Server URL' field is a note: 'This may be referred to as "URL" or "Address" in your streaming software.' Below the 'Stream Key' field is a note: 'Stream keys are valid for 7 days. Once you start to preview the broadcast you have up to 5 hours to go live.' At the bottom right of the form is an 'Event Logs' button.

Live Stream Setup
Copy and paste these settings into your streaming software.

Server URL
rtmps://live-api-s.facebook.com:443/rtmp/ Copy
This may be referred to as "URL" or "Address" in your streaming software.

Stream Key
1015749241979640186_sw=0&s_vt=api-s&a=AbxzXDAZs Copy
Stream keys are valid for 7 days. Once you start to preview the broadcast you have up to 5 hours to go live.


Event Logs

Facebook will give you two parameters, "stream key" and "server URL"

Step 3:


Fill these two parameters into the "Host Address" and "Stream Name" of the camera. Then click enable and save.

1. Please also ensure that the camera has the latest firmware loaded. Please check www.alfatronelectronics.com for the latest firmware.
2. Copy the complete Server url into the Host Address Field
3. Change the port number to match the server url ie: 443
4. Insert the Stream Key into the Stream Name Field
5. Click Enable and Save



Step 4:

If the camera has an audio input, please enable audio on the 'Audio Configuration' settings on the camera.



Step 5:

Once it has been set up as per above, the stream will be live on YouTube.

