



# ROLLS

## MX51s 4-Channel Mixer

- Studio
- Live
- Broadcast

Anywhere you need to mix up to four signals to a single output.

### SPECIFICATIONS

|                  |                                   |
|------------------|-----------------------------------|
| Input Impedance: | 10K $\Omega$ unbalanced each jack |
| CH 1 Gain:       | 32 dB XLR jack (highest gain)     |
| Phantom Power:   | for CH 1 microphone XLR           |
| CH 2 Gain:       | 26 dB 1/8" and RCA                |
| CH 3 and 4 Gain: | 26 dB each RCA                    |
| Output:          | 1/8" stereo and stereo RCA        |
| S/N Ratio:       | >90 dB                            |
| THD:             | <.008%                            |
| IMD(SMPTE):      | <.008%                            |
| Power:           | ROLLS PS27s 15 VDC adapter        |
| Weight:          | 1 lbs. (.45 Kg)                   |
| Size:            | 3" x 5" x 1.25" (8 x 13 x 3.2 cm) |

### What's in the box?

- 1 - Made in USA MX51s
- 1 - 15V power supply PN PS27s
- 1 - This owners manual