

AC70 Battery Charger

EQUIP Wireless System



AC70 Charger

Key Features and Benefits

- · 4-port quick charger
- Charges 4 batteries simulatenously
- 4 battery storage slots
- · LED status indicator lights
- Charge time is 2 hours
- Charges BAT70 lithium-ion batteries
- Desktop or wall mount options
- Wireless Connection to Base Station provides battery charging status

The EQUIP™ wireless intercom system operates in the 5 GHz band and provides exceptional audio quality with low noise and excellent radio propagation even in challenging RF environments.

Description

The AC70 Smart Battery Charger can charge up to four BAT70 lithium-ion batteries simultaenously. LEDs at the charging ports indicate battery status. Charge time is approximately two hours. The AC70 can be placed on a desktop or mounted on a wall.

Technical Specifications

Power Supply

Input Voltage: 100 - 240V AC nomimal

Output Voltage: 5V; 4A MTBF: 300,000 hours calculated Charge Output: ~ 3W per port

Battery Charger

Input Voltage: 5V; 4A

Charge Output: ~3W per port

Wireless

Wireless PAN, 2.4 GHz Wireless Technology

Front / Top Panel

Four charging ports for BAT70

LED type: 4xRGB, for port/battery charging

status

Side Panel

Four storage ports for BAT70 (Storage ports do not charge)

Environmental


Operating: 32° to 104°F (0° to 40°C) Storage: -40° to 80°F (-40° to 176°C) Humidity: 0-95% Non-Condensing



AC70 Battery Charger

EQUIP Wireless System

AC70 Charging



AC70 Mounting



Order Codes

AC70: Smart Battery Charger BAT70: Lithium-ion Battery CON-00004: Power Supply

EQUIP System Bundles

EQP-3UP-US: (3) User bundle w/ headsets: 2Ch, 5GHz, US **EQP-3UP-EU:** (3) User bundle w/ headsets: 2Ch, 5Ghz, EU EQP-3UP-AU: (3) User bundle w/ headsets: 2Ch, 5GHZ, AU EQP-3UP-KR: (3) User bundle w/ headsets: 2Ch, 5GHZ, KR EQP-3UP-JP: (3) User bundle w/ headsets: 2Ch, 5GHZ, JP EQP-5UP-US: (5) User bundle w/ headsets: 2Ch, 5GHZ, US EQP-5UP-EU: (5) User bundle w/ headsets: 2Ch, 5GHZ, EU EQP-5UP-AU: (5) User bundle w/ headsets: 2Ch, 5GHZ, AU EQP-5UP-KR: (5) User bundle w/ headsets: 2Ch, 5GHZ, KR EQP-5UP-JP: (5) User bundle w/ headsets: 2Ch, 5GHZ, JP





